

# Covert Antenna Systems

## Stealth Magnetic Mount

Available In VHF, VHF/UHF & VHF/7-800

- Low profile, durable and covert
- Easily move from vehicle to vehicle
- Now available for software defined radios
- Secured by three high powered magnets



MODEL NUMBER	CMAG-SB-VHF	CMAG-DB-VHF/UHF	CMAG-DB-VHF/7-800
Frequency Range (MHz)	150-174	150-174/406-512*	150-174* / 760-870
Bandwidth (MHz)	24	24* 34*	24* / 136
Power Rating (watts)	150		150 35
Finish	Black		
Max. Height (in.)	9.6		
Mounting Hole (in.)	Magnet Mount		
Feed Line (17' ea)	RG 174	RG58	
Connectors (choose one)	PL259, Mini-UHF, BNC, TNC, SMA, N, QMA		